

Aqara Hub M2

Το Aqara Hub M2 είναι ένα κέντρο έξυπνου σπιτιού. Μπορεί να συνδεθεί με δίκτυο WiFi ή Ethernet και υποστηρίζει αλληλεπίδραση και σύνδεση με αξεσουάρ Aqara Zigbee. Έχει επίσης λειτουργία IR τηλεχειριστηρίου, η οποία μπορεί να προσθέσει και να διαχειριστεί τον έλεγχο διαφορετικών συσκευών IR. Το Aqara Hub M2 σας επιτρέπει να ελέγχετε τα αξεσουάρ Aqara με μεγαλύτερη ευκολία.

- Υποστήριξη Zigbee 3.0, έως 128 συσκευές*: Υποστηρίζει όλες τις πιο πρόσφατες συσκευές Aqara βασισμένες στην ταχύτερη, πιο σταθερή και ενεργειακά αποδοτική τεχνολογία.
- Έλεγχος Υπέρυθρων 360°: Ελέγξτε τις υπάρχουσες συσκευές IR από οποιοδήποτε σημείο του δωματίου σας μέσω φωνής** και μέσω τοπικών αυτοματισμών.
- Θύρα Ethernet RJ-45: Ενσύρματη σύνδεση μέσω Ethernet RJ-45 για επιπλέον σταθερότητα και μικρότερο χρόνο απόκρισης.
- Ενσωματωμένος Ηχείο: Μπορεί να χρησιμοποιηθεί ως συναγερμός ή κουδούνι μέσω προσαρμόσιμων αυτοματισμών.
- Τροφοδοσία μέσω USB: Πιο ευέλικτη εγκατάσταση και προαιρετική εφεδρική μπαταρία χάρη στην υποστήριξη τροφοδοσίας Micro-USB 5V 1A.
- Πλήρης Συμβατότητα: Χρησιμοποιήστε τον αγαπημένο σας φωνητικό βοηθό** ή το οικοσύστημα έξυπνου σπιτιού μαζί με τους αυτοματισμούς της εφαρμογής Aqara Home.
- Υποστήριξη όλων των 4 τρόπων ξυπνητηριού του Apple HomeKit.

*Μέχρι 128 παιδικές συσκευές Aqara Zigbee μπορούν να συνδεθούν στο κέντρο (απαιτούνται συσκευές επαναλήπτες όπως Smart Plug και Wall Switch (με ουδέτερο)).

**Υποστηρίζονται οι φωνητικοί βοηθοί Apple Siri, Amazon Alexa, Google Assistant και άλλοι.

Προδιαγραφές:

Μοντέλο: HM2-G01

Διαστάσεις: φ100.5×30.75 χιλιοστά (φ3.95×1.21 ίντσες)

Τροφοδοσία: 5V 1A ή 5V 2A

Ασύρματο Πρωτόκολλο: Wi-Fi IEEE 802.11 b/g/n 2.4GHz, Zigbee3.0 IEEE 802.15.4, BLE 5.0

Θερμοκρασία Λειτουργίας: -5°C~+50°C (23°F~122°F)

Υγρασία Λειτουργίας: 0%-95%RH, χωρίς συμπύκνωση

Υποστήριξη Συστήματος: Android 6.0 ή iOS 12.0 και νεότερες εκδόσεις

Συχνότητα Λειτουργίας Wi-Fi: 2412-2472 MHz

Μέγιστη Ισχύς Εξόδου Wi-Fi < 20 dBm

Συχνότητα Λειτουργίας Bluetooth: 2402-2480 MHz

Μέγιστη Ισχύς Εξόδου Bluetooth < 13 dBm

Συχνότητα Λειτουργίας Zigbee: 2405-2480 MHz

Μέγιστη Ισχύς Εξόδου Zigbee < 13 dBm

Περιεχόμενα Συσκευασίας: Κέντρο M2 × 1, Εγχειρίδιο Χρήστη × 1, Καλώδιο Micro USB σε USB-A × 1.

Aqara Hub M2

The Aqara Hub M2 is a smart home control center. It can be connected with a WiFi or Ethernet network, and supports interaction and connection with Aqara Zigbee accessories. It also has an IR remote control function, which can add and manage the control of different IR devices. The Aqara Hub M2 allows you to control your Aqara accessories more conveniently.

- **Zigbee 3.0 Support, up to 128 devices***: Supports all the latest Aqara devices based on the fastest, most stable, and energy-efficient technology.
- **360° Infrared Control**: Control your existing IR devices from any part of your room by voice** and via local automations.
- **Ethernet RJ-45 Port**: Wired connection via Ethernet RJ-45 for extra stability and lower response time.
- **Built-in Speaker**: Can be used as an alarm or doorbell via configurable automations.
- **USB Power**: More flexible installation and optional battery backup thanks to Micro-USB 5V 1A power support.
- **All-Round Compatibility**: Use your favorite voice assistant** or smart home ecosystem together with Aqara Home app automations.
- **Support of all the 4 Apple HomeKit native alarm modes.**

*Up to 128 Aqara Zigbee child devices can be connected to the hub (repeater devices such as Smart Plug and Wall Switch (with Neutral) are required).

**Apple Siri, Amazon Alexa, Google Assistant, and more are supported.

Specifications:

Model: HM2-G01

Dimensions: $\phi 100.5 \times 30.75 \text{ mm}$ ($\phi 3.95 \times 1.21 \text{ in.}$)

Input Power: 5V 1A or 5V 2A

Wireless Protocol: Wi-Fi IEEE 802.11 b/g /n 2.4GHz, Zigbee3.0 IEEE 802.15.4, BLE 5.0

Operating Temperature: $-5^{\circ}\text{C} \sim +50^{\circ}\text{C}$ ($23^{\circ}\text{F} \sim 122^{\circ}\text{F}$)

Operating Humidity: 0%-95%RH, no condensation

Support System: Android 6.0 or iOS 12.0 and above

Wi-Fi Operation Frequency: 2412-2472 MHz

Wi-Fi Maximum Output Power < 20 dBm

Bluetooth Operation Frequency: 2402-2480 MHz

Bluetooth Maximum Output Power < 13 dBm

Zigbee Operation Frequency: 2405-2480 MHz

Zigbee Maximum Output Power < 13 dBm

What's in the Box: Hub M2 $\times$ 1, User Manual $\times$ 1, Micro USB to USB-A cable $\times$ 1.