

32 Charges

1.8 Hours

Cutting Machine (1100W) 1.7 Hours



Circular Saw (1400W) 1.3 Hours



0

Camera (16Wh) 118 Charges

48 Charges

Car Fridge (60W)

33 Hours

Coffee Maker (1000W) 1.9 Hours 1.2 Hours

D Electric Kettle (1500W)



Light (10W) 60 Hours





14 Hours















EcoFlow was founded in 2017 with a mission is to empower people and communities through portable, clean, reliable power for lasting impact by dethroning the traditional gas generator and reinventing the way the world accesses energy.

We leverages our technology and experience to build products that are thoughtful in design, creating industry-first, smart and powerful energy storage products, and strive to reinvent the way people everywhere access power.

## **EcoFlow Technology Ltd.**

Email: sales@ecoflow.com

Website: https://ecoflow.com/



# **DELTA Max**



Backup your home during power outages with DELTA Max. With an expandable capacity that reaches up to 6kWh, dual charging, and the ability to power most of your home devices, you can stay powered on in any situation.

## Expands up to 6048Wh

A single DELTA Max unit packs a 2kWh capacity that is expandable up to 6kWh with DELTA Max Smart Extra Batteries. This means when a blackout hits, you can continue to power your important home devices such as your fridge and lights for hours on end.

## Rapid dual charging

DELTA Max charges up safely and rapidly from 0-80% in just 1 hour. Or get up to 3600W speeds by combining AC charging and the EcoFlow Smart Generator.

## Powers 99% of appliances

With EcoFlow's X-Boost technology, DELTA Max can power heavy-duty devices up to 3000W. That means during a power outage or blackout, you can continue to power your fridge, dryer, and more. That's the industry gold standard for a portable power station of this size and capacity.

# Specification

# **DELTA Max**

#### General

Model Name	DELTA Max (2000)	DELTA Max (1600)
Capacity	2016Wh	1612Wh
Extra Battery	Support up to two D Extra Battery/Smart	ELTA Max Smart Generator

## Output

a lead ready to the control developer	2400W total	2000W total
AC Output(×4)	(Surge 4600W)	(Surge 4600W)
Max Device(s) Power Suppoerted by X-Boost	3000W	2500W
USB-A Output (×2)	5V, 2.4A, 12W Max	<
USB-A Fast Charge (×2)	5V, 2.4A / 9V, 2A	/ 12V, 1.5A, 18W Max
USB-C Output(×2)	5/9/12/15/20V, 5A	4, 100W Max
Car Power Output(×1)	12.6V, 10A, 126W 1	Max
DC5521(×2)	12.6V, 3A	

## Input

AC Charging	2000W	1600W
Solar Charging	800W Max, 11-10	00Vdc, 10A
Car Charging	Supports 12V/24V Battery, Default 8A	

## **Battery**

Battery Chemistry	NCM	
Cycle Life	800 cycles to 80%+ capacity	500 cycles to 80%+ capacity
Shelf Life	1 year	

#### Other

Connectivity	Wi-Fi supported
Dimension	14.9 × 7.2 x 9.4in / 37.8 × 18.4 x 24cm
Weight	48lbs / 22kg

# **DELTA Max Smart Extra Battery**



#### General

Capacity	2016Wh
Dimension	18.3 x 9.3 x 11.1in / 46.4 x 23.5 x 28.3cm
Weight	40lbs / 18kg

## **Battery**

Battery Chemistry	NCM
Cycle Life	800 cycles to 80%+ capacity
Shelf Life	1 year

# **Charging Time**



1.6 Hours

(2000W)



Gas Generator\* 1.6 Hours (2000W)

Solar Panel

3.2-6.3 Hours (2×400W Solar Panel)



Car Charger 21 Hours (96W)

## **Solar Panel Recommendations**

Solar Panels	Recharge Time
110W Solar Panel	3 Sets: <b>7.5-15 hrs</b>
	4 Sets: <b>5.6-11.2 hrs</b>
160W Solar Panel	1 Set: 17-34 hrs Recommended when portability matters
	2 Sets: <b>8.5-17 hrs</b>
	3 Sets: <b>5.6-11.2 hrs</b>
	4 Sets: <b>4.2-8.4 hrs</b>
400W Solar Panel	1 Set: <b>3-6 hrs</b>
	2 Sets: <b>3.2-6.3 hrs</b> Recommended when quality time matter

<sup>\*</sup>The data above is for DELTA Max (2000) only.

<sup>&</sup>quot;The rated output power of the gas generator should be higher than the power station max AC input power.